

PRIMA-VA/680W

Order no.: 1001531

PRODUCT INFORMATION

PRIMA-VA/680W is a wall-mounted public address and voice alarm controller certified in accordance with EN 54-16 and EN 54-4. It offers specific features for small to medium-sized installations.
PRIMA-VA/680W integrates six highly efficient Class D amplifiers and one battery charger. It is capable of handling a loudspeaker output power of up to 80 watts per zone. One amplifier can also be used as a backup amplifier.

PRIMA-VA/680W is based on matrix control functions and digital message players, with front-panel access for full monitoring of the fireman?s microphone and the emergency message trigger button. The controller incorporates our latest “Flexcontrol” technology, offering extensive system configuration options. Various settings can be freely assigned to the six potentiometers.

The controller features eight monitored logic control inputs, eight relay outputs, two interfaces for paging consoles such as the PSS-G2 and PSM8WJB, two balanced audio inputs for connecting sources such as music players and wireless microphones, one audio output for control by external devices, one Ethernet port, and six independent amplifier outputs. A 5-pin XLR connector for the optional monitored PRIMA-VA/FM fireman?s microphone is located on the front panel.

Thanks to its IP connectivity, the PRIMA-VA/W offers maximum flexibility. The system is SIP-compatible and can communicate with the complete range of ATEÏS Vox@ Audio-over-IP products as well as the Vox@net g2 Audio-over-IP software. This also enables networking with additional

sources and devices.

Up to 256 PRIMA-VA/W systems can be interconnected. From a standalone solution to an IP-networked application, the PRIMA-VA/W system can be easily adapted to a wide range of applications.

Thanks to its web browser interface, the PRIMA-VA/680W can be configured for both basic and advanced applications. Numerous parameters, including volume control, priorities, source selection, and others, can be configured via the web browser.

The PRIMA-VA/680W voice alarm system is certified in accordance with EN 54-16. All components and peripheral devices are continuously monitored, and all events, including faults and alarms, are recorded in a history log that can be accessed via a web browser.

Digital controller with six integrated Class D amplifiers and battery charger

- Six monitored Class D amplifiers
- 250 W output power per channel
- 800 W maximum total output power across all outputs
- Integrated battery charger
- Up to six loudspeaker zones, up to five loudspeaker zones with one backup amplifier, or up to three A/B loudspeaker zones
- Simultaneous distribution of six different audio sources to six zones
- Continuous loudspeaker line monitoring
- Freely assignable functions for the six potentiometers
- Up to four simultaneous IP audio streams
- Up to four message players
- Message storage capacity of more than one hour in MP3 format
- IP connectivity compatible with Vox@ and Vox@net g2
- Easy integration into IP PBX systems via SIP
- Up to 256 PRIMA-VA systems can be interconnected
- SNMP protocol for remote monitoring
- Audio output for control by external devices
- Certified in accordance with EN 54-16 and EN 54-4
- Wall-mounted design

Manufacturer information
ATEÏS Deutschland GmbH
Bahnhofstr. 18
74906 Bad Rappenau
Germany
info.de@ateis.global
www.ateis-deutschland.de

Safety Notes and Warning Messages
The unit uses dangerous mains voltage. Leave servicing to skilled personnel only and do not

insert anything into the air vents. Inexpert handling may result in electric shock.
During operation, there may be a hazard of contact with a dangerous voltage of up to 100 V at the speaker terminals. Always switch off the amplifier before making or changing any connections.
Do not operate the unit and disconnect the mains plug from the socket immediately if the unit or the mains cable is visibly damaged; if a defect might have occurred after the unit was dropped or suffered a similar accident, if malfunctions occur. In any case, the unit must be repaired by skilled personnel.
The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).
Never pull the mains cable to disconnect the mains plug from the socket, always seize the plug.
The heat generated inside the unit must be dissipated by air circulation; never cover the air vents of the housing.
If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

SPECIFICATIONS

PRIMA-VA/680W	
Peak output power	800 W
Power rating	800 W
Power rating at 100 V	6 x 250 W
Zones	6
Inputs	3.8 V/22 kΩ (mic/line)
Frequency range	20-20,000 Hz
S/N ratio	87 dB
THD	< 0.2%
Power supply	˜ 110-230 V/50-60 Hz optional battery DC 24 V/60 Ah
Mains voltage	~ 115-230 V
Mains frequency	50-60 Hz
Admiss. ambient temp.	-10 °C to +50 °C
Width	570 mm
Height	780 mm
Depth	200 mm
Weight	26.6 kg
Connections	Plug-in screw terminals (audio inputs) 5-pole XLR (optional fire brigade microphone) Plug-in screw terminals (outputs) 1 x RJ45 (ethernet)

PRIMA-VA/680W

Packaging dimensions (W x H x L)	0.78 × 0.2 × 0.54 m
Gross weight	27 kg
Net weight	26.6 kg

PRIMA-VA/680W

EAN code	3760439320953
Net weight	26.6 kg