# TXS-626

Order no.: 0253520

## PRODUCT INFORMATION

**2-channel multifrequency receiver unit,**
with UHF PLL technology.

- 1,000 selectable UHF frequencies (672.000-696.975 MHz) for each channel (10 groups with 100 frequencies each)
- ACT function for transmitting selected frequency to pocket transmitter TXS-606HSE/2, tie clip microphone transmitter TXS-606LT/2, desktop microphone transmitter TXS-606DT/2 or hand-held microphone TXS-606HT/2 via infrared signal
- Auto-scan
- True diversity system with removable antennas (BNC connection)
- Volume and squelch controls for each channel
- Each channel with LCD for indicating group/channel, antenna A/B, RF receiving level, AF audio level and additional LED level display for indicating audio level
- XLR output for each channel, bal.
- 6.3 mm output for mixed signal
- 8 V supply voltage for active antennas or antenna amplifier (e.g. TXS-875B) is available
- Robust metal housing
- Supplied with power supply
- 482 mm (19") rack installation, 1 RU

**There are restrictions or requirements within the EU!**

**Please read the notes regarding wireless systems in the section “IMPORTANT INFORMATION”!**

**Manufacturer information:**
MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

**Safety Notes and Warning Messages**

The unit uses dangerous mains voltage. Leave servicing to skilled personnel only and do not insert anything into the air vents. Inexpert handling may result in electric shock.

Do not operate the unit and disconnect the mains plug from the socket immediately if the unit or the mains cable is visibly damaged; if a defect might have occurred after the unit was dropped or suffered a similar accident, if malfunctions occur. In any case, the unit must be repaired by skilled personnel.

The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).

Never pull the mains cable to disconnect the mains plug from the socket, always seize the plug.

If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

## SPECIFICATIONS

**TXS-626**

**General information**

| | |
|---|---|
| Description | receiver unit |
| Carrier frequency range | 672.000-696.975 MHz |
| Audio frequency range | 30-18,000 Hz |
| Channels | 2 |
| THD | < 0.5% |
| Dynamic range | 100 dB |
| RF S/N ratio | 105 dB |
| Admiss. ambient temp. | 0-40 °C |

**Specifications receiver**

| | |
|---|---|
| Audio signal receiver | 350 mV/600 Ω (jack)25 mV/600 Ω (XLR, bal.) |
| Power supply receiver | via encl. plug-in power supply |
| Width receiver | 482 mm |
| Height receiver | 45 mm |
| Depth receiver | 195 mm |
| Weight receiver | 1.8 kg |
| Connections receiver | 2 x XLR, bal., 1 x 6.3 mm jack, unbal. |

**TXS-626**

| | |
|---|---|
| EAN code | 4007754223514 |
| Net weight | 2.082 kg |