G-7SET

Order no.: 0250760

PRODUCT INFORMATION

Pair of professional dual-band transceivers,
case set,
consisting of 2 transceivers with belt clip, 2 clip-on mics with earphones, charger for 2 transceivers, 2 rech. battery packs.

- 8 PMR channels 446 MHz
- 69 LPD channels 433 MHz
- Boost function for a wide operating range
- High-performance rech. batteries for high operational availability
- Manual transmit mode (PTT) or hands-free voice-activated transmit mode (VOX)
- Monitoring function
- Automatic squelch
- Channel scan mode (SCAN)
- CTCSS tones
- Dual watch
- Vibracall function
- Key lock
- Backlit LCD
- Supplied in a robust hard-sided case

Licence-free, please refer to instruction manual on the MONACOR website.

Manufacturer information:
Alan Electronics GmbH
Daimlerstrasse 1 g
63303 Dreieich
Germany
info@albrecht-midland.de

Safety Notes and Warning Messages

Remove the rechargeable batteries or batteries if the device is not in use for a longer period of time (e.g. more than a week). This avoids possible damage through leaking batteries.
If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.
Batteries and rechargeable batteries must not be disposed of with household waste. They must be disposed of in accordance with local regulations for hazardous waste.

SPECIFICATIONS

G-7SET

General information

Description	hand-held transceiver set
Carrier frequency range	446.00625-446.09375 MHz (PMR)433.075-434.775 MHz (LPD)
Channels	1
Admiss. ambient temp.	-20 °C to +55 °C
Power supply	4 x rech. battery AA size, 800 mAh
Dimensions	58 x 195 x 34 mm
Total weight	1.203 kg
Connections	2.5 mm jack (microphone) 3.5 mm jack (speaker)

Specifications transmitter

Transmitting power	500 mW
Operating range	≤ 5,000 m

G-7SET

EAN code	8011869203916
Net weight	1.203 kg