SPR-6

Order no.: 0210640

PRODUCT INFORMATION

Stereo phono anti-distortion preamplifier acc. to RIAA,
for connecting a turntable to the aux input or line input of a hi-fi system, a mixer or an amplifier, etc. Low hum effect due to metal case and supplied plug-in power supply.

Manufacturer information:
MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages
The unit uses dangerous mains voltage. Leave servicing to skilled personnel only and do not insert anything into the air vents. Inexpert handling may result in electric shock.
Do not operate the unit and disconnect the mains plug from the socket immediately if the unit or the mains cable is visibly damaged; if a defect might have occurred after the unit was dropped or suffered a similar accident, if malfunctions occur. In any case, the unit must be repaired by skilled personnel.
The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).
Never pull the mains cable to disconnect the mains plug from the socket, always seize the plug.
If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

SPECIFICATIONS

SPR-6	
Description	anti-distortion preamplifier
Frequency range	20-20,000 Hz
Input signal	5 mV/47 kΩ

SPR-6

Output signal	450 mV/100 kΩ
S/N ratio	> 50 dB
Admiss. ambient temp.	0-40 °C
Power supply	via encl. plug-in power supply
Dimensions	67 x 37 x 121 mm
Weight	200 g
Inputs	1 x RCA L/R
Outputs	1 x RCA L/R

SPR-6

EAN code	4007754099461
Net weight	0.262 kg